Tender text

SA-440/SW

Universal stereo mixing amplifier, 100 W

Mixing made easy! An easy-to-use operating concept and clearly arranged features. Two stereo line sources and two mono microphone sources can be mixed together without any problems. Each input channel features a tone control. The master output levels can be preadjusted via recessed trimming potentiometers in order to protect them against overload. An optional remote switch can mute the stereo master outputs and the power amplifier.

- Silent operation due to fanless cooling concept
- 2 stereo line inputs
- 2 balanced microphone inputs
- Parallel stereo line input on the front panel
- 3-way equalizer for each microphone input
- Common 2-way tone control for the two line inputs
- Muting via optional momentary push-button/switch
- 2 adjustable stereo master outputs
- Master output level can be preadjusted via trimming potentiometers
- Adjustable headphone output
- Stereo record output
- LEDs for indicating overload (clip)
- 482 mm (19") rack installation, 1 RS, with supplied mounting brackets

Specifications:

Peak output power	2 x 100 W
Power rating	100 W
Power rating at 4 Ω	2 x 50 W
Power rating at 8 Ω	2 x 30 W
Channels	2
Inputs	125 mV/10 kΩ (line) 1.3 mV/600 Ω (mic)
Frequency range	20-20,000 Hz
Equalizer bass	± 12 dB/30 Hz
Equalizer midrange	± 12 dB/1 kHz (voice only)
Equalizer treble	± 12 dB/12 kHz
S/N ratio	> 60 dB
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	220 VA
Admiss. ambient temp.	0-40 °C
Width	432 mm
Height	52 mm
Depth	275 mm
Rack spaces, RS	1
Weight	3.5 kg
Connections	3 x RCA L/R (line),

2 x 6.3 mm jack, bal. (mic),
2 x RCA L/R (master),
1 x RCA L/R (rec.),
1 x plug-in screw terminal (mute),
4 x spring-load. speaker term. (speakers)

Brand: MONACOR

Type: SA-440/SW

Quantity: 1

Packing dimensions (W x H x L): 0.34 x 0.11 x 0.46 m

Gross weight: 5.22 kg

Net weight: 4.7 kg

Item weight (w/o accessories): 3.5 kg